



NEOS TECHNOLOGIES

A Gooch & Housego Company

MODEL NUMBER:

21035-.4AM

SPECIFICATIONS

Document Number: **56A17075**

The 21035-.4AM OEM Module Is A RF Driver With Analog Modulation Input And A 0.4 Watt Output Into A 50 Ohm Load.

PARAMETER:

SPECIFICATION:

Output Frequency:	35.000 MHz \pm 0.01% Quartz Stabilized
Spurious Levels:	-50 dBc Maximum
Harmonic Distortion:	-15 dBc Maximum
Analog Input:	\pm 1 Volt into 50 Ohms \pm 1 Volt = Full RF Power 0 Volt = Minimum RF Power
Extinction Ratio:	50 dB Minimum
RF Rise	30 ns Maximum P_{RF} : 10 to 90 %
Fall Time	30 ns Maximum P_{RF} : 90 to 10 %
RF Output Power:	0.4 Watts Nominal Adjustable Factory Set for Optimum Performance When Paired with a NEOS AO Device.
Output Impedance:	50 Ohms Nominal
Supply Voltage:	+ 24 VDC \pm 0.5 Volt
Supply Current:	1 Amp Maximum

MAXIMUM RATINGS:

Supply Voltage:	+ 28 Volts
Power Output:	No DC Feedback Allowed
Case Temperature:	+ 55 ⁰ C The Driver Must Be Attached to an Adequate Heatsink.

CONNECTORS & MECHANICAL:

RF Output Connector:	BNC Female
Modulation Input Connector:	BNC Female
Power Supply Connections:	Vcc Solder Post Return Ground Lug
Physical Size:	4.8" L x 1.61" H x 3.87" W

RELATED DOCUMENTS:

Outline Drawing:	53B2384	Acceptance Test Procedure:	42A17056
Operating Manual:	51A14096	Acceptance Test Results Form:	52A17094

For More Information, Contact: neos@neostech.com Ph. (321) 242-7818 Fax (321) 242-1019